

# S2 Dust extractor



Article code	Voltage
S201-EU	230V, 50 Hz

Technical data	
Motor	2×1200 W
Amperage	9.8
Air flow	400 m <sup>3</sup>
Vacuum (kPa)	22
Pre filter	Conical polyester
Pre filter surface	3 m <sup>2</sup>
HEPA filter	H13
HEPA filter surface	2.4 m <sup>2</sup>
Jet puls filter cleaning	Yes
Collection	Longopac

Physical parameters	
Weight	52 Kg
Size	761×547×1300 mm

Pairing with Von Arx machines	
With <b>VA 10 L</b>	With <b>FR 200</b>

Equipped with
2-stage industrial by pass motors
Conical polyester Pre filter
Hepa13 rated Hepa filter
Jet puls filter cleaning
7,5m 2" hose
Wand
Floor tool with rubber blades
Longopac collection

# Spare parts

<p><b>Conical prefilter - 7500016</b></p> 	<p><b>Hepa filter - 7500000</b></p> 	<p><b>Longopack - 7500017</b></p> 
<p><b>Longopac holder - 7000016</b></p> 	<p><b>Wand-7500142</b></p> 	<p><b>Floor tool - 7500143</b></p> 
<p><b>Rubber squeegees, pair - 7509996</b></p> 	<p><b>Hose end cuff 2" - 7500018</b></p> 	<p><b>Connector D51 hose with V sealing - 800161</b></p> 
<p><b>Hose set D50 mm x 7,5m- 7001064</b></p> 	<p><b>Front casters - 7500165</b></p> 	<p><b>Rear wheels - 7500014</b></p> 
<p><b>Soft start 230V - 7500172</b></p> 	<p><b>Soft start 120V - 7500196</b></p> 	<p><b>Soft start 230V S3 - 7500137</b></p> 
<p><b>Motor 230V - 7500020</b></p> 	<p><b>Motor 120V - 7500168</b></p> 	<p><b>On/Off switch - 7500001</b></p> 